

Zivan NG1 Charger 48V 25A



Reference : ZIV-NG1-48V-25A

Brand : ZIVAN

Options :

No variants

3D Model : Available

EAN-13 : 3760123456789

Manufacturer Part Number (MPN): GGELCB-07000X | **Brand**: ZIVAN

The **ZIVAN NG1 CAN BUS 48V 25A charger** is an industrial high-frequency charger designed for **48 V** traction battery charging. It is a solid choice for projects searching for a **48V lithium battery charger** (subject to BMS compatibility and configuration) as well as for lead-acid batteries (depending on settings). Its **CAN BUS** connectivity enables integration into modern architectures where a **BMS** supervises or actively manages the charging process.

This product is supplied as the **charger unit only** (NG1). Batteries, BMS, vehicle/machine-specific harnesses, and operator interfaces are not included, allowing engineering teams full flexibility for **system sizing and integration** (battery choice, protections, cabling, HMI, safety chain, etc.).

Key benefits

- Professional solution rated **48 V / 25 A** for low-voltage traction applications.
- Suitable as a **48V lithium battery charger** when the BMS defines/validates the charging profile (configuration-dependent).
- **Isolated CAN BUS** interface with **CANopen** compatibility for BMS / master-system communication.
- **Programmable** charging curves and possible external control for advanced integration.
- High efficiency (> 85%) helps reduce losses and heat generation.
- Integrated safety functions: output short-circuit protection, reverse polarity protection, acoustic alarm.
- Internal logging up to **1000 charge cycles** (useful for maintenance/diagnostics).
- Compact form factor for fixed or onboard integration (environment/IP to be considered).

Technical specifications

Parameter	Value
Technology	High-frequency switched-mode charger controlled by microcontroller
Product type	Industrial charger with CAN BUS communication
Main operating range	48 V (traction use; lithium/lead-acid compatibility depends on configuration and BMS)
Kit nominal power	Not applicable (charger only)
Maximum power (indicative)	≈ 1.2 kW (indicative; depends on battery voltage and charging regime)
Controller max current	Not applicable
Main motor	Not applicable
Total kit mass	≈ 2.2 kg
Operating environment	-20 °C to +50 °C; forced-air cooling; IP20 (protected enclosure/area recommended)
Control interfaces / Connections	Isolated CAN BUS, CANopen compatible (communication with BMS/PC/master system)
Power cabling	To be sized by the integrator (current/lengths); verify crimping, routing, and protections
Protection and main disconnect	To be provided: upstream protection, accessible disconnect, safety chain (application-dependent)
Dimensions / Footprint	≈ 300 × 160 × 80 mm (indicative)
Compliance	CE (LVD / EMC) – final compliance depends on full system integration
Integration country	Italy (manufacturer)

Typical applications

- Light electric vehicles (industrial, utility, specialty).
- Material handling and low-voltage traction equipment.
- Aerial platforms, mobile machines, industrial carts.
- Industrial cleaning machines (scrubbers, sweepers).
- 48V electric marine applications (environment/ventilation/protection to be validated).
- Retrofit/conversion projects where the lithium BMS manages charging via CAN.

Recommended integration

- Validate **battery chemistry** (e.g., LiFePO₄) and the charging strategy defined by the BMS.
- Confirm **protocol compatibility** (CAN/CANopen) and expected frames (charge enable, current/voltage limits, etc.).
- Configure charging curves by trained personnel (lead-acid/lithium settings, safety thresholds, temperature compensation if used).
- Install the charger with adequate **airflow** (IP20: protected enclosure/area recommended).
- Size DC power cabling (cross-sections, crimping, labeling) and avoid unnecessary lengths.
- Implement protections: suitable fuses/breaker, contactor/main disconnect, and application-specific safety chain.
- Take EMC into account: routing, bonding/grounding, separation of power and control, shielding if required.

- Plan diagnostic access (maintenance, log reading, configuration/update if applicable).
- Document schematics, BOM, and configuration parameters for traceability.

Operating conditions

- Respect the allowed battery voltage range and BMS/configuration under/over-voltage thresholds.
- In hot environments, consider **thermal derating**: airflow and installation strongly impact performance.
- IP20: avoid dust/water/spray; use a protected location or a ventilated enclosure.
- Provide an **accessible disconnect** and emergency stop in line with the final application.
- Perform periodic checks: torque, heating points, cable/crimp condition, and air inlet cleanliness.
- Regulatory compliance (EMC, machinery, road/marine) depends on the complete integrated system.
- Configuration/diagnostic operations must be carried out by trained personnel.

Specifications are provided for technical guidance and may depend on configuration, battery type (lead-acid/lithium), BMS behavior, and integration conditions (cabling, airflow, environment). Final validation (performance, safety, compliance) remains the responsibility of the integrator.

© EVEA Distribution – All rights reserved – contact@evea-solutions.com

This document is the exclusive property of EVEA Distribution. Any reproduction or distribution, even partial, is prohibited without prior written authorization.

The information contained in this datasheet is provided for information purposes only and may be modified without notice. This document does not constitute a contractual commitment.